

R&S® AirLancer ON-QT60

60° outdoor Wi-Fi sector antenna with 4x4 MIMO



The weatherproof R&S® AirLancer ON-QT60 sector antenna with a beam angle of 60° is ideal for Wi-Fi coverage over larger areas, such as warehouses and factories. With 4x4 MIMO support, it ensures maximum performance for reliable Wi-Fi client connectivity in difficult environments, especially where reflections and scattering occur. Due to its tri-band capability on all four ports, this antenna is perfect for mixed operation in the 2.4, 5, and 6 GHz bands.

- ▶ WLAN sector antenna with approx. 90° beam angle and +7 dBi gain in 2.4 GHz, 5 GHz, and 6 GHz
- ▶ 4x4 MIMO technology for reliable WLAN coverage in harsh environments
- ▶ Future-proof due to support of the new 6 GHz band
- ▶ Mounting kit for wall and pole mounting, cable and adapter included
- ▶ Connects to R&S® LANCOM indoor access points via the adapter R&S® AirLancer AN-RPSMA-NJ
- ▶ Especially suitable for use with the R&S® LANCOM outdoor access points OX-6402 and OW-602


R&S® AirLancer ON-QT60

Technical Information	
Frequency range	2400 MHz - 2500 MHz and 4900 – 7125 MHz
Impedance	50 Ohm
Polarization	-45°, +45°, -45°, +45°
Gain	7 dBi @ 2,4 GHz and 7 dBi @ 5/6 GHz
Half-Power-Beam-Width horizontal	60° @ 2.4 GHz and 60° @ 5 GHz
Half-Power-Beam-Width vertical	60° @ 2.4 GHz and 60° @ 5 GHz
VSWR	typ. 1.5:1 - max. 2.0:1
Mechanical Information	
Connectors & Cables	4 x 100cm UV stable ULA100 cable with N-Plug
Dimensions	233.7mm x 183.7mm x 40mm
Weight	0.9 kg
Housing material	UV resistant plastic
Color	lightgray
Operating temperature	-40° to 85°C
Article	
Recommended use case	Point-to-Multipoint radio links / Sector coverage
Mounting material	articulating wall and pole mount accessories included
Support	
Warranty	2 years support
Accessories	
Antenna cable	R&S® AirLancer cable NJ-NP 3m, item no. 61230, R&S® AirLancer cable NJ-NP 6m, item no. 61231, R&S® AirLancer cable NJ-NP 9m, item no. 61232
Adapter	R&S® AirLancer AN-RPSMA-NJ adapter to connect ON Antennas to R&S® LANCOM Indoor Access Points and IAPs, item no. 61259
Surge arrester (antenna cable)	R&S® AirLancer SurgeProtect surge arrester (2.4 and 5 GHz), to be integrated between Access Point and antenna, item no. 61257
Fit for the following LANCOM devices	
Outdoor	R&S® LANCOM OW and OX series (with external antenna connectors)
Indoor	All R&S® LANCOM Indoor Access Points and IAPs via separately available Adapter R&S® AirLancer AN-RPSMA-NJ*
*) Note	You need one adapter per antenna connector
Item number(s)	
R&S® AirLancer ON-QT60	61263


R&S® AirLancer ON-QT60

Antenna Gain (combined gain of all antenna elements)

2.4 GHz, Azimuth Plane




2.4 GHz, Elevation Plane




R&S® AirLancer ON-QT60

Antenna Gain (combined gain of all antenna elements)

5.25 GHz, Azimuth Plane




5.25 GHz, Elevation Plane




R&S[®] AirLancer ON-QT60

Antenna Gain (combined gain of all antenna elements)

5.6 GHz, Azimuth Plane



5.6 GHz, Elevation Plane



Rohde & Schwarz Networks and Cybersecurity GmbH
Adenauerstr. 20/B2
52146 Wuerselen | Germany
info.rs-nc@rohde-schwarz.com | www.rohde-schwarz.com/networks-and-cybersecurity

R&S and Rohde & Schwarz are trademarks of Rohde & Schwarz GmbH & Co. KG, registered or used, among others, in Germany, the EU, the USA, China, and other countries. Other names or designations used may be registered trademarks of different companies or owners. This document contains forward-looking statements regarding products and product features. The publisher reserves the right to change these at any time without stating reasons. No liability is accepted for technical inaccuracies or omissions. 07/2026

ROHDE & SCHWARZ
Make ideas real

